AES standard for digital audio – Digital input-output interfacing – Transmission of digital audio over asynchronous transfer mode (ATM) networks

Published by *Audio Engineering Society, Inc.* Copyright ©2005 by the Audio Engineering Society

Abstract

This document specifies the method of carrying multiple channels of audio in linear PCM or AES3 format in calls across an asynchronous transfer mode (ATM) network to ensure interoperability. The specification includes the method of conveying information concerning the format and sampling frequency of the digital audio signal when setting up the calls.

An AES standard implies a consensus of those directly and materially affected by its scope and provisions and is intended as a guide to aid the manufacturer, the consumer, and the general public. The existence of an AES standard does not in any respect preclude anyone, whether or not he or she has approved the document, from manufacturing, marketing, purchasing, or using products, processes, or procedures not in agreement with the standard. Prior to approval, all parties were provided opportunities to comment or object to any provision. Attention is drawn to the possibility that some of the elements of this AES standard or information document may be the subject of patent rights. AES shall not be held responsible for identifying any or all such patents. Approval does not assume any liability to any patent owner, nor does it assume any obligation whatever to parties adopting the standards document. This document are invited to submit, with their comments, notification of any relevant patent rights of which they are aware and to provide supporting documentation.

Document preview: for full document, go to www.aes.org/publications/standards

2011-10-17 printing

AES47-2006 (r2011)

Contents

0 Introduction 4 0.1 Background 4 0.2 Patents 5 0.3 Conventions used in this document 5 0.4 Reserved bits 6 1 Scope 6 2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5 Autoe call connection: SETUP and ADD PARTY messages 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6.1 Qualifying information 15 6.2 Subtrame format 15 6.3 Asampling frequency. 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 19 8.1 Message encapsulation 19	Foreword	3
0.1 Background 4 0.2 Patents 5 0.3 Conventions used in this document 5 0.4 Reserved bits 6 1 Scope 6 2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message tormat and action to be taken by recipient 19 8.3 Message tormat and action	0 Introduction	4
0.2 Patents 5 0.3 Conventions used in this document 5 0.4 Reserved bits 6 1 Scope 6 2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message incapsulation 19 8.3 Message incapsulation 19 8.4 Message input efferences 25 Annex B (informative) Data protection	0.1 Background	4
0.3 Conventions used in this document 5 0.4 Reserved bits 6 1 Scope 6 2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message format and action to be taken by recipient 19 8.4 Message types 19 8.4 Message types	0.2 Patents	5
0.4 Reserved bits 6 1 Scope 6 2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 12 9.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 8.1	0.3 Conventions used in this document	5
1 Scope	0.4 Reserved bits	6
2 Normative references .6 3 Definitions and abbreviations .7 4 Format of audio data in ATM cells .8 4.1 Format of audio samples .8 4.2 Packing of sample data into cells .10 4.3 Formats .11 1.4 ATM adaptation layer .12 4.5 ATM-user-to-ATM-user indication .12 5 Switched virtual circuits .12 5.1 ATM addresses .12 5.2 Audio call connection: SETUP and ADD PARTY messages .12 5.3 Call disconnection .15 6 Encoding of audio formats .15 6.1 Qualifying information .15 6.2 Subframe format .15 6.3 Packing of subframes into cells .16 7 Permanent virtual circuits .17 8 Management interface .17 8.1 Call connection: SETUP messages .17 8.2 Message iormat and action to be taken by recipient .19 8.3 Message format and action to be taken by recipient .19 8.4 Message types .19 Annex A Informative references .25 Annex B (informative) Data protection .26	1 Scope	6
2 Normative references 6 3 Definitions and abbreviations 7 4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe tormat 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Package torpsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 A Informative references 26 Annex A Informative references 26 <tr< td=""><td></td><td></td></tr<>		
3 Definitions and abbreviations	2 Normative references	6
4 Format of audio data in ATM cells 8 4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26	3 Definitions and abbreviations	7
4 Format of audio data in A fix cens	4 Format of audio data in ATM calls	°,
4.1 Format of audio samples 8 4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 16 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 <td< td=""><td>4 Format of audio data in ATM cens</td><td>0</td></td<>	4 Format of audio data in ATM cens	0
4.2 Packing of sample data into cells 10 4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	4.1 Format of audio samples	8
4.3 Formats 11 4.4 ATM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	4.2 Packing of sample data into cells	10
4.4 A I IM adaptation layer 12 4.5 ATM-user-to-ATM-user indication 12 5 Switched virtual circuits 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	4.3 Formats	
4.5 ATM-USEF-TO-ATM-USEF Indication 12 5 Switched virtual circuits 12 5.1 ATM addresses 12 5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	4.4 A I M adaptation layer	
5 Switched virtual circuits125.1 ATM addresses125.2 Audio call connection: SETUP and ADD PARTY messages125.3 Call disconnection156 Encoding of audio formats156.1 Qualifying information156.2 Subframe format156.3 Packing of subframes into cells166.4 Sampling frequency167 Permanent virtual circuits178 Management interface178.1 Call connection: SETUP messages178.2 Message encapsulation198.3 Message format and action to be taken by recipient198.4 Message types19Annex A Informative references25Annex B (informative) Data protection26B.1 Sequence number26B.2 Audio data26Annex C (informative) Application Identifier values27	4.5 ATM-USET-to-ATM-USET indication	12
5.1 ATM addresses125.2 Audio call connection: SETUP and ADD PARTY messages125.3 Call disconnection156 Encoding of audio formats156.1 Qualifying information156.2 Subframe format156.3 Packing of subframes into cells166.4 Sampling frequency167 Permanent virtual circuits178 Management interface178.1 Call connection: SETUP messages178.2 Message encapsulation198.3 Message format and action to be taken by recipient198.4 Message types19Annex A Informative references25Annex B (informative) Data protection26B.1 Sequence number26B.2 Audio data26Annex C (informative) Application Identifier values27	5 Switched virtual circuits	12
5.2 Audio call connection: SETUP and ADD PARTY messages 12 5.3 Call disconnection 15 6 Encoding of audio formats 15 6 I Qualifying information 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	5.1 ATM addresses	12
5.3 Call disconnection 15 6 Encoding of audio formats 15 6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	5.2 Audio call connection: SETUP and ADD PARTY messages	12
6 Encoding of audio formats 15 6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	5.3 Call disconnection	15
6.1 Qualifying information 15 6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	6 Encoding of audio formats	15
6.2 Subframe format 15 6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	6.1 Qualifying information	15
6.3 Packing of subframes into cells 16 6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	6.2 Subframe format	
6.4 Sampling frequency 16 7 Permanent virtual circuits 17 8 Management interface 17 8 Management interface 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	6.3 Packing of subframes into cells	16
7 Permanent virtual circuits 17 8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	6.4 Sampling frequency	16
8 Management interface 17 8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	7 Permanent virtual circuits	17
8.1 Call connection: SETUP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	8 Management interface	
8.1 Can connection. SETOP messages 17 8.2 Message encapsulation 19 8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	8 1 Call connection: SETTLE mossages	17
8.3 Message format and action to be taken by recipient 19 8.4 Message types 19 Annex A Informative references 25 Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	8.2 Massage encapsulation	/ ۱ 10
8.4 Message types	8.2 Message format and action to be taken by recipient	
Annex A Informative references	8.4 Message types	19
Annex A Informative references		
Annex B (informative) Data protection 26 B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	Almex A informative reletences	20
B.1 Sequence number 26 B.2 Audio data 26 Annex C (informative) Application Identifier values 27	Annex B (informative) Data protection	26
B.2 Audio data	B.1 Sequence number	26
Annex C (informative) Application Identifier values	B.2 Audio data	26
	Annex C (informative) Application Identifier values	27
Document preview:	Document preview:	

2011-10-17 printing

Foreword

[This foreword is not a part of AES standard for digital audio – Digital input-output interfacing – Transmission of digital audio over asynchronous transfer mode (ATM) networks, AES47-2002.]

This document was developed under project AES-X92, Digital Audio in Asynchronous Transfer Mode (ATM). It is derived from draft X92-PWD-JG-010617, prepared by J. Grant for task group SC-02-02-E, incorporating the result of the task group meeting on 2001-06-12.

The membership of the task group was K. Brown, C. Chambers, J. Dunn, P. Eastty, C. Gaunt, J. Grant, U. Horbach, H. Lemcke, G. Mills, M. Schindele, J. M. Strawn, T. Thompson, and M. Yonge.

The task group has prepared a report for AESSC SC-02-02 of guidelines for AES47-2002, AES standard for digital audio - Digital input-output interfacing – Transmission of digital audio over asynchronous transfer mode (ATM) networks which has now been published as AES-R4-2002, Guidelines for AES standard for digital audio – Digital input-output interfacing – Transmission of digital audio over asynchronous transfer mode (ATM) networks, AES47.

Julian Dunn, chair Robert A. Finger, vice-chair SC-02-02

Foreword to 2006 revision

This revision of AES47 was prepared under project AES47-R by task group SC-02-02-E. It specifies use of the Organisationally Unique Identifier 00-0B-5E, recently acquired by AESSC, in 5.2.2.2 and 8.1.2.2. It also simplifies the minimum requirements to ensure interworking, in clause 4.3.

The membership of the task group at the time of writing the second edition was K. Brown, R. Caine, C. Chambers, P. Eastty, C. Gaunt, J. Grant, U. Horbach, H. Lemcke, M. Page, M. Schindele, J. M. Strawn, T. Thompson, J. Waas, and M. Yonge.

John Grant, chair Robert A. Finger, vice-chair SC-02-02

Addendum 2010-02-19

A new multi-part revision of AES3 was published in 2009. Its technical content is intended to be identical to the relevant parts of the 2003 edition as amended by Amendment 5 (2008) and Amendment 6 (2008). Where this document refers to clauses of earlier editions of AES3, equivalent references to AES3-2009 are also offered, *[identified by italic text in square brackets]*.

Note on normative language

NOTE In AES standards documents, sentences containing the verb "shall" are requirements for compliance with the document. Sentences containing the verb "should" are strong suggestions (recommendations). Sentences giving permission use the verb "may." Sentences expressing a possibility use the verb "can."

Document preview: for full document, go to www.aes.org/publications/standards

AES standard for digital audio – Digital input-output interfacing – Transmission of digital audio over asynchronous transfer mode (ATM) networks

0 Introduction

0.1 Background

This document describes means for the transmission of professional audio across digital networks, including metropolitan- and wide-area networks, to provide the best performance with regard to latency, jitter, and other relevant factors.

Current-generation wide-area communications are based on two very similar systems, synchronous optical network (SONET) and synchronous digital hierarchy (SDH), SONET being used in the United States and SDH in Europe. On top of them are run integrated services digital network (ISDN), asynchronous transfer mode (ATM), and Internet protocol (IP).

ISDN provides telephone call connections of a fixed capacity which carry one 8-bit value per $125 \mu s$; when a call is set up, its route through the system is chosen, and the switches that route the data are configured accordingly. Each link, between switches or between switch and end equipment, is formatted into frames that take $125 \mu s$ to transmit, and each data byte is identified by its position in the frame.

ATM, also called broadband ISDN, provides a service similar to ISDN, but with the capacity of each call being specified by the caller. Links are formatted into cells, which consist of a header and 48 data bytes; the header is typically 5 bytes long, and most of it is taken up with the virtual channel identifier (VCI) that shows to which call the cell belongs. Call setup, routing, and switching are done in the same way as in ISDN, but with calls not being restricted to 1 byte every $125 \,\mu$ s.

IP provides a very different service, not designed for continuous media such as audio and video. There is no call setup, and each packet contains enough information within itself to allow it to be routed to its destination. This means that the header is much larger than in the case of ATM, typically 74 bytes, and packets will also typically be much larger, if only because otherwise the overheads would be excessive. Each packet is liable to be routed separately, so two packets that are part of the same flow may well take different routes. This can mean that the one that was sent first does not arrive first.

For many professional audio applications, a round-trip time from the microphone through the mixing desk and back to the headphones of no more than 3 ms is required. Allowing 0,5 ms each for conversion from analog to digital and

AES47-2006 (r2011)

back again, it follows that the network connections to and from the mixing desk must have a latency of less than 1 ms each. For distances of more than about 200 km, the transmission delay alone will exceed 1 ms, but within a metropolitan area the transmission delay should be no more than 0,25 ms (equivalent to about 50 km), leaving 0,75 ms for packetization, queuing within switches, and resynchronization within the receiving equipment.

Packetization delays are proportional to the size of the transmission unit (frame, cell, or packet), and resynchronization delays depend on how evenly spaced the transmission units are when they arrive at their destination. Both classes of delay are thus small for ISDN and large for IP. Using the format specified in this document to carry dual-channel AES3 audio with a 48 kHz sampling frequency over ATM results in an inter-cell time of $125 \,\mu$ s, at which ATM will have similar delays to ISDN. A higher sampling frequency or a larger number of channels would reduce the inter-cell time and hence also the delays.

The queuing time within each ISDN switch is likely to be around one frame time, or $125 \ \mu$ s. The ATM documents limit the queuing time in an ATM switch to approximately the inter-cell time for the call, which, as with the other delays, translates into performance similar to that of ISDN for dual-channel 48 kHz AES3 audio and better for higher sampling frequencies or larger numbers of channels.

The queuing time within an IP router for normal, best effort, Internet traffic is unbounded, and if the router is congested, packets may simply be thrown away. Resource reservation protocol (RSVP) (see annex A) allows capacity to be reserved for a particular traffic flow, but it does not guarantee that the packets will actually be routed over the links on which the capacity has been reserved; if the flow is re-routed, it will only get a best effort service until a reservation has been made on the new route, and it may not even be possible to make a reservation on the new route at all.

ATM has therefore been chosen as providing a more convenient service than ISDN and significantly better performance than IP, even when RSVP is used.

This document does not specify a physical interface to the network because one of the features of ATM is its ability to make a seamless connection between interfaces operating at a wide variety of data rates and with different ways of encoding the ATM cells. Commonly used interfaces provide 25,6 Mbit/s over category 3 structured wiring and 155,52 Mbit/s over category-5 structured wiring or fibre-optic cable.

The physical layer section description and unique ATM abbreviations can be found in ATM forum approved specifications. See annex A.

0.2 Patents

Attention is drawn to the possibility that some of the elements of this AES document may be the subject of patent rights not identified herein. The AES shall not be held responsible for identifying any or all such patent rights.

0.3 Conventions used in this document

0.3.1 Decimal points

According to International Electrotechnical Commission (IEC) directives, the comma is used in all text to indicate the decimal point. However, in specified coding, including the examples shown, the full stop is used, as in IEC programming language standards.

0.3.2 Data representation

In this document, all coding and data representations are printed in an equally spaced font.

0.3.3 Non-printing characters

Non-printing characters are delimited by angle brackets, as in <CR> for carriage return.

0.4 Reserved bits

Unless otherwise indicated, bit assignments shown as reserved are reserved for future standardization by the AES, only by means of amendment or revision of this document.

1 Scope

This document specifies a means to carry multiple channels of audio in linear PCM or AES3 format over an ATM layer service conforming to ITU-T Recommendation I.150. It includes a means to convey, between parties, information concerning the digital audio signal when setting up audio calls across the ATM network.

It does not specify the physical interface to the network.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

AES3-2003 AES standard for digital audio engineering — Serial transmission format for two-channel linearly represented digital audio data.

AES10-2003 AES recommended practice for digital audio engineering — Serial multi-channel audio digital interface (MADI).

AES11-2003 AES recommended practice for digital audio engineering – Synchronization of digital audio equipment in studio operations.

ITU-T Recommendation I.150 (02/99) B-ISDN asynchronous transfer mode functional characteristics. Geneva, CH: International Telecommunications Union.

ITU-T Recommendation I.363.5 *B-ISDN ATM adaptation layer specification: Type 5 AAL*. Geneva, CH: International Telecommunications Union.

ITU-T Recommendation Q.2931 (02/95) - Digital Subscriber Signaling System No. 2 (DSS 2) – User-Network Interface (UNI) layer 3 specification for basic call/connection control. Geneva, CH: International Telecommunications Union.

ITU-T Recommendation Q.2971 (10/95) - Broadband integrated services digital network (B-ISDN) – Digital subscriber signaling system No. 2 (DSS 2) – User-network interface layer 3 specification for point-to-multipoint call/connection control. Geneva, CH: International Telecommunications Union.

OUI and company_id assignments. See the resource locator on the databases page of http://www.aes.org/standards/.